

DELTA DELUXE JAMMA WIRING CHART

Function	Wire Colour	PIN	PIN	Function	Wire Colour
GROUND	BLACK	1	A	GROUND	BLACK
GROUND	BLACK	2	B	GROUND	BLACK
+5	RED	3	C	+5	RED
+5	RED	4	D	+5	RED
+5	GREEN	5	E	+5	GREEN
+12	YELLOW	6	F	+12	YELLOW
		7	H		
COIN METER 1	PURPLE	8	J	COIN METER 2	GREY
		9	K		
SPEAKER (+)	LIGHT BROWN	10	L	SPEAKER (-)	PINK
		11	M		
VIDEO RED	RED	12	N	VIDEO GREEN	GREEN
VIDEO BLUE	BLUE	13	P	VIDEO SYNC	WHITE
GROUND	BLACK	14	R	SWITCH	ORANGE
TEST	GREEN	15	S		
COIN A	BLUE	16	T	COIN B	WHITE
START	BROWN	17	U	START	LIGHT BROWN
UP	RED	18	V	UP	RED
DOWN	ORANGE	19	W	DOWN	ORANGE
LEFT	YELLOW	20	X	LEFT	YELLOW
RIGHT	GREEN	21	Y	RIGHT	GREEN
BUTTON 1	BLUE	22	Z	BUTTON 1	BLUE
BUTTON 2	PURPLE	23	a	BUTTON 2	PURPLE
BUTTON 3	GREY	24	b	BUTTON 3	GREY
BUTTON 4	WHITE	25	c	BUTTON 4	WHITE
BUTTON 5	PINK	26	d	BUTTON 5	PINK
GROUND	BLACK	27	e	GROUND	BLACK
GROUND	BLACK	28	f	GROUND	BLACK

# DELTA DELUXE JAMMA WIRING DIAGRAM

